

8 3 5 5 W

1/2 HP AC BELT DRIVE WI-FI® GARAGE DOOR OPENER

Reliable and secure with the convenience of built-in Wi-Fi.



WARRANTY

LIFETIME
Motor and Belt

1-YEAR
Parts and
Accessories

RELIABLE
SMART
SECURE

P3
MOTORS®

1/2 HP AC MOTOR IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

BELT DRIVE SYSTEM FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

MOTOR VIBRATION ISOLATION SYSTEM (MVIS®) PROVIDES QUIET, RELIABLE OPERATION.

myQ®

FREE MyQ® MOBILE APP SO USERS KNOW THEIR HOME IS SECURE.

BUILT-IN WI-FI FOR THE EASIEST WAY TO CONNECT THE GARAGE.

REAL-TIME ALERTS INDICATE THE STATUS OF THE GARAGE DOOR VIA EMAIL OR PUSH NOTIFICATIONS.

MONITOR AND CONTROL THE OPENER FROM ANYWHERE USING MOBILE DEVICES.

Security+ 2.0®

SAFEGUARDS GARAGE ACCESS BY SENDING A NEW CODE WITH EVERY CLICK.

POSILOCK® ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

ALERT-2-CLOSE SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ.

THE PROTECTOR SYSTEM® INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

INCLUDED ACCESSORIES:

MULTI-FUNCTION CONTROL PANEL®

Turns on garage door opener lights from inside the garage.



882LMW

3-BUTTON REMOTE CONTROL

Operates up to 3 openers or MyQ Light Accessories.



8931LM

PROTECTIVE ADD-ONS:

REMOTE LIGHT CONTROL

Enables home lighting control through a garage remote or a smartphone.



8255LM

GARAGE DOOR AND GATE MONITOR

Monitors and closes up to 4 garage doors from any room in the house.



8299LM

MINI UNIVERSAL REMOTE CONTROL

Compact and portable to provide quick, easy garage access.



374UT

WIRELESS KEYLESS ENTRY

Provides convenient, secure access from outside the garage with a 4-digit PIN.



877MAX

PRODUCT GUIDE 8355W

1/2 HP AC BELT DRIVE
WI-FI GARAGE DOOR OPENER

LiftMaster
PREMIUM SERIES

MASTERFUL ENGINEERING.

MOTOR

- 1/2 Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection

POWER

- 120VAC
- 60 Hz Voltage
- 6A Current Rating
- UL Listed
- 4' Power Cord (3-Prong)

MECHANICS

- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **AC Wi-Fi Logic Board** with Built-In Surge Suppressor



DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	128"	140"	164"
Max. Opening	7'6"	8'6"	10'6"

Headroom Clearance Required: 2"

8"

Per second for door to move upward

SPEED

8"

Per second for door to move downward

STANDARD SPECS.

SECURITY

SECURITY+ 2.0®

RADIO CONTROLS

3-Button Remote Control (893LM)

Operating Range: **~200'**

Operating Temperature: -30°F to 150°F

- Remote Control: 310, 315 and 390 MHz Tri-Band
- Garage Door Opener: Frequency Agile on 310, 315 and 390 MHz
- Security+ 2.0 Rolling Code Technology

SECURITY+ 2.0

ENCRYPTED CONTROLS

Multi-Function Control Panel® (882LMW)

- Program Remote Controls
- Maintenance Alert System
- Easy Wi-Fi Setup

SMART

MyQ® RADIO



- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER*)

*May require an external adapter depending on the model and year of your vehicle. Visit HomeLink.com for additional information.

ELECTRICAL

LIGHTING



- Max. 2 100-Watt Lightbulbs
- Adjustable Time
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

ENERGY EFFICIENCY

- Approximately 1.5-Watt Power in Standby Mode*
- *Occurs at Down Limit When Opener's Lights Turn Off

SHIPPING.

SHIPPING WEIGHT (in lbs.)



CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Multi-Function Control Panel (882LMW)
- 3-Button Remote Control (893LM)
- Garage Door Opener Head (8355W)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5"

- Assembled Solid-Steel Belt T-Rail

CONVENIENCE AND SAFETY.



- Alert-2-Close/Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Safety Beam Obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 24 Remote Controls, 2 Wireless Keyless Entry Systems and 16 MyQ Devices